


# LED 数码显示 PAR 灯使用说明

## LED DIGITAL DISPLAY PAR LIGHT INSTRUCTION

### 1. 图解部分:

Diagram part:



- A. 功能键 (Function Key)
- B. 参数加键 (Parameter increase key)
- C. 参数减键 (Parameter reduce key)
- D. 保存键 (Save Key)

1.1 恢复出厂设置, 长按 A 键 3 秒, 显示器显示 DEFA, 表示恢复出厂设置成功, 客户自定义功能全部恢复到出厂默认这种参数。

Factory reset, long press A key for 3 seconds, the display will be display DEFA, it means factory reset is ok. The whole functions of Customer's user-defined are back to factory reset.

1.2 保存功能: 按一下 D 键, 相应功能在显示器中闪三下, 表示保存成功, 每次上电开机, 就会默认进入保存成功的功能。

Save function: Press D key, the corresponding functional will be flash three times in the display, it means ok, every time power on, it is default enter into save successful function.

### 2. LED 显示窗功能对照表, (所有的功能选定后再按一次 D 键保存确认即可)

Led displayer function comparison table. (All the functions are selected and then press an D save can be confirmed)

序号 NO.	显示 DISPLAY	功能说明 Function specification
1	d0001	地址码, (001—512) B、C 键加减地址码数值 Address Code (001—512) B、C key Plus&Minus number.
2	P050	七彩跳变, (00—255) B、C 键修改跳变速度 Colorful jump, (00—255) B、C key amend jump speed.
3	L050	七彩渐变, (00—255) B、C 键修渐变速度 colorful gradients, (00—255) B、C key amend gradients speed.
4	E050	七彩脉变, (00—255) B、C 键修改脉变速度 Colorful pulse change, (00—255) B、C key amend change speed.
5	soud	七彩声控变化 Colorful voice control change
6	R255	红色选色, (000—255) B、C 键修改亮度 Red colour selection, (000—255) B、C key amend brightness
7	G255	绿色选色, (000—255) B、C 键修改亮度 Green colour selection, (000—255) B、C key amend brightness
8	B255	蓝色选色, (000—255) B、C 键修改亮度 Blue colour selection, (000—255) B、C key amend brightness
9	H255	白色选色, (000—255) B、C 键修改亮度 White colour selection, (000—255) B、C key amend brightness
10	F255	频闪, (000—255) B、C 键修改闪烁频率 Strobeflash, (000—255) B、C key amend flash frequency

### 3.DMX512 通道说明

#### DMX512 channel Specification

序号 NO.	功能 Function	说明 specification
第1通道 The first channel.	总调光 master light-dimmer	R、G、B、H总调光，线性调光，由暗到亮 R、G、B、H master light-dimmer, linear dimming, from dark to bright.
第2通道 The second channel	R 调光 R light-dimmer	R 调光，线性调光，由暗到亮 R light-dimmer, linear dimming, from dark to bright.
第3通道 The third channel	G 调光 G light-dimmer	G 调光，线性调光，由暗到亮 G light-dimmer, linear dimming, from dark to bright
第4通道 The fourth channel	B 调光 B light-dimmer	B 调光，线性调光，由暗到亮 B light-dimmer, linear dimming, from dark to bright.
第5通道 The fifth channel	H 调光 H light-dimmer	H(白)调光，线性调光，由暗到亮 H(white)light-dimmer, linear dimming, from dark to bright.
第6通道 The sixth channel	功能选择 Function choose	0—50: 频闪和线性调光; 51—100: 跳变; 101—150: 渐变; 151—200: 脉变; 201—255: 声控 0—50: Strobeflas and light-dimmer, 51—100: jump change, 101—150: gradients change, 151—200: pulse change, 201—255: Voice change.
第7通道 The sevsnth channel	功能速度 Function speed	对应第6通道功能的速度，由慢到快 Correspond to the sixth channel function speed, from slow to fast.

### 4.电流调整 Current regulation

用户可方便再次调整输出电流大小:

User can convenience to adjust output current again.

可通过软件设置来调整, 长按 (D 保存键) 保持 5 秒钟方可进入, 设置完成后再按一次 (D 保存键) 便可保存退出, 操作对应表如下:

User can use software set to adjust, long press (D save key) for 5 second to enter, selected and then press D save can be confirmed. The operating table as follow:

序号 NO.	显示 Display	功能说明 Function Specification
1	RL150	红色电流, (00—99) B、C 键修改限流大小, 数值增加电流减小 Red current, (00—99) B、C amend current magnitude, numerical increase current decrease
2	GL00	绿色电流, (00—99) B、C 键修改限流大小, 数值增加电流减小 Green current, (00—99) B、C amend current magnitude, numerical increase current decrease
3	BL00	蓝色电流, (00—99) B、C 键修改限流大小, 数值增加电流减小 Bluc current, (00—99) B、C amend current magnitude, numerical increase current decrease
4	HL00	白色电流, (00—99) B、C 键修改限流大小, 数值增加电流减小 White current, (00—99) B、C amend current magnitude, numerical increase current decrease